

| | | | |
|-----|--|----------|--|
| CH2 | Movement control sound/auto | 0--64 | Auto play single scene, CH4 can select scene through CH3 to select effect library |
| | | 65-127 | Automatically loop all scenes in the selected effect library, and select the effect library through CH3 |
| | | 128-191 | Sound control plays single scenes. You can select scenes through CH4 and select effect library through CH3 |
| | | 192-255 | Sound control loop plays all scenes in the selected effect library. Select the effect library through CH3 |
| CH3 | Effect library selection(15 values as one library) | 0--15 | 1 library |
| | | 16--31 | 2 library |
| | | | |
| | | 192--223 | 15 library |
| | | 224--255 | 0 library |
| CH4 | Scene selection | 0--255 | Every value is corresponding to each pattern, value is much bigger than the pattern, system marked it as the biggest pattern |
| CH5 | Color selection | 0-31 | Full color |
| | | 32-63 | Red |
| | | 64-95 | Yellow |
| | | 96-127 | Green |
| | | 128-159 | Cyan |
| | | 160-191 | Blue |
| | | 191-223 | Purple |
| | | 224-255 | White |
| CH6 | Movement speed | 0 | Default effect speed |
| | | 1-15 | Patterns don't move (several patterns will move slowly) |
| | | 16-255 | Movement speed goes from slow to fast |

34CH content shown as follows:

| 34CH Content | | | |
|--------------|--|-----------|--|
| Channel | Function | DMX value | Content |
| CH1 | Pattern1 OFF/ON | 0 | OFF/ON |
| | | 1-99 | Auto mode |
| | | 100-199 | Sound mode |
| | | 200-254 | Reserve |
| | | 255 | Pattern A off light, Pattern B allowed to be on |
| CH2 | Pattern goes out of range/Pattern size | 0-49 | Pattern goes out of the range |
| | | 50-99 | Pattern comes back of the range |
| | | 100-149 | Pattern is hidden when it goes out of the range |
| | | 150-199 | Pattern zooms in, and hidden when it goes out of the range |
| | | 200-255 | Reserve |
| CH3 | Effect library selection(15 values as one library) | 0--15 | 1 library |
| | | 16--31 | 2 library |
| | | | |
| | | 192--223 | 15 library |
| | | 224--255 | 0 library (cell phone APP effect library) |
| CH4 | Pattern selection | 0--255 | Every value is corresponding to each pattern, value is much bigger than the pattern, system marked it as the biggest pattern |
| CH5 | Pattern zoom | 0 | No zoom |
| | | 1-31 | Zoom effect 1 |
| | | 32-47 | Zoom effect 2 |
| | | | |
| | | 224-255 | Zoom effect 8 |
| CH6 | Pattern rotation | 0-63 | Manual control rotation |