JLPOW COB Par Light

User Manual



Thank you for choosing JLPOW COB par light which features RGB colors and multi-function. Whenever you go dancing or to a show, it can fuel your passion and create the best visual atmosphere. The manual describes how to use it and the safety issues. Please read it carefully and keep it as your reference.

A. Specifications:

- Power Voltage: AC100V-240V / 50-60 Hz

- Power Consumption: 15W

- LED: 1 * 15W 3 in 1 LED (Red / Green / Blue)

- Mode: Auto / Voice-activated / DMX / Master-slave

- Channel: 6CH

Beam Angle: Approx. 25°Dimming: 0% - 100%LED Life: 10000 Hours

Connector: 3 Pin XLRShell Material: ABS PlasticProduct Weight: 0.97lb / 439g

- Size: 4.7*4.7 *3.5 inch / 11.93*11.93*8.9 cm

B. Package Includes

1 x Par Light

1 x Remote Control

1 x User Manual

D. DMX Control: 6 Channels

Channel	Value	Functional Description		
CH1	0-255	Master Dimming (CH5-CH6)		
CH2	0-255	Red Light – From Dark to Bright		
СНЗ	0-255	Green Light - From Dark to Bright		
CH4	0-255	Blue Light - From Dark to Bright		
CH5	0-5	Need to Use with CH1-CH4		
	6-255	Strobe Mode, From Slow to Fast		
СН6	0-50	OFF		
	51-90	Jump Mode		
	91-130	Color Selection		
	131-170	Gradual Mode		
	171-210	Auto Mode		
	211-255	Sound Activated Mode		

C. Operating Instructions:



Menu - Mode Selection Up - Value Added Down - Value Subtracted Enter - Confirmation

Menu	Numerical	Description		
d001	d001-d512	DMX Address		
IP.01	IP.01- IP.73	Slave Mode		
A1.01	A1.01- A1.07	Color Selection*		
A2.00	A2.00- A2.20	Jump Mode, Adjust Speed 00-20, press "enter" button to save your settings		
A3.00	A3.00- A3.20	Gradual Mode, Adjust Speed 00-20, press "enter" button to save your settings		
A4.00	A4.00- A4.20	Auto Mode, Adjust Speed 00-20, press "enter" button to save your settings		
A5.00	A5.00- A5.20	Sound Activated Mode, Adjust Sound Sensitivity 00-20, press "enter" button to save your settings		
FF.00	FF.00- FF.20	Strobe Mode, Adjust Speed 00-20		
r000	r000-r255	Red Brightness(Dark-Bright)		
G000	G000- G255	Green Brightness (Dark-Bright)		
b000	b000- b255	Blue Brightness (Dark-Bright)		

*Color Selection Details: (A1)

No.	Color	No.	Color	No.	Color
A1.01	Red	A1.02	Green	A1.03	Blue
A1.04	Yellow	A1.05	Purple	A1.06	Light blue
A1.07	RGB (White)				

E. Note

- Please keep it safe from falling and dropping.
- Confirm the supplied voltage is stable and required.
- Indoor use only, please do waterproof measures if outdoor use.
- Keep away from Children. Please do not look at the light directly, in case it might damage the eyes.

F. Feedback

We appreciate your 5-star feedback and positive comments if you are satisfied with our products! If you have any questions or problems, feel free to contact with **support@jlpow.com**. We take care of every feedback from you, and strive to perfect our product all the times.